

Recommend Bria client configuration for Clearfly SIP service:

Note: Some settings below may not be available depending upon the capabilities of your device.

1. Tap/click “Add Account”
2. Select “Clearfly Comm” from the list of SIP providers
3. Enter the following settings in the main “Edit Account” view:

Setting	Value
Display As	<Enter your name here>
Username	<Typically your phone number>
Password	<The password provided by Clearfly>
Domain	v.cfly.co
VM Number	*98

Now Tap/click the “Account Advanced” menu option and set the following values:

Setting	Value
Outbound Proxy	<empty>
Authorization Name	<empty>
Send DTMF using	RFC 2833
Suppress STUN Wi-Fi	Checked
Suppress STUN Mobile	Checked
Use ICE Wi-Fi	Unchecked
Use ICE Mobile	Unchecked
Global IP Wi-Fi	Checked
Global IP Mobile	Checked
SIP Transport	UDP
Encrypt Audio	Never
Refresh Interval	900
Use Tel Uri	Unchecked
Single Register	Unchecked
Connection Reuse	Checked
Passive Session Timer	Checked
Enable IMS	Unchecked
Wi-Fi Interval	30
Mobile Interval	9